



## SC403 Standalone RFID Access Control Terminal

SC403 is an innovative Proximity card reader used in Access Control applications and can be installed standalone or with any third party panel that supports 64-bit Wiegand.

User will benefit from their unparalleled performance using the state of the art proximity reader and embedded Linux platform.

## SC 405



- Stores 30000 cards and 50000 transactions
- ▶ Read Cards and or/PINs
- Built in Serial and Ethernet ports
- Multi Language Support
- Built in Bell scheduling
- Audio-Visual indications for acceptance and rejection of valid/invalid cards
- ▶ 4 x 4 metal keypad with 4 function keys
- SDK available for OEM customers and software developers.

\*Disclaimer: Features and technical specifications are subject to change without notice.

# > Technical Specifications

Capacity

#### Verification/Identification

| Templates:    | 30000 | Matching:        | 1:N up to 30000 users |
|---------------|-------|------------------|-----------------------|
| Transactions: | 50000 | Verification:    | ≤1 second             |
|               |       | Identification:  | ≤2 seconds            |
|               |       | Enrollment time: | ≤5 seconds            |
|               |       | FRR:             | ≤1%                   |
|               |       | FAR:             | ≤0.001%               |

#### Display

#### Environment

| LCD | 4 X 16 Characters LCD Display | Oper. Temp:     | 32°-105°F (0°-42°C) |
|-----|-------------------------------|-----------------|---------------------|
|     |                               | Oper. Humidity: | 20%-80%             |



| Port: | RS 232(10M)/ RS 485(1.2km) | Oper. Voltage: | 12V DC |
|-------|----------------------------|----------------|--------|
| Port: | Ethernet 10/100            | Oper. Current: | 400 mA |
| Port: | Mini-USB 2.0 port          |                | I      |

#### Dimensions

Options

| Proximity | Mifare |
|-----------|--------|
| HID       |        |

### Part Numbers

| SC403     | SC403 Proximity Terminal          |
|-----------|-----------------------------------|
| SC403-M   | SC403 Terminal with Mifare Reader |
| SC403-HID | SC403 Terminal with HID Reader    |

# Installation Diagram

Standalone



